

FireFighter is the newest innovation from Encore Controls Inc. It is the easiest, most cost effective way to add fire alarm monitoring to your Honeywell or 2GIG control panel. FireFighter's unique technology monitors the existing UL smoke detectors within the home. When an alarm is detected a wireless signal is sent to the control panel which in turn contacts the central monitoring station. With interconnected hardwired smoke detectors found in most homes today, only one FireFighter is needed to monitor ALL the smoke detectors within the home.

FEATURES

- Monitors any UL existing smoke detector
- Does not impact UL or Fire Marshall approval of existing smoke detectors
- 100% compatible with 2GIG panels and Honeywell 5800 receivers
- Uses 1 CR123A long life lithium battery
- FCC, IC, and ETL listed in US and Canada to UL985 standard



SPECS

- Frequency: 345MHz
- Battery: 3V lithium CR123A
- Battery life: 5 years
- Detection distance: 6 in max
- Operating Temperature: 32°-120°F (0°-49°C)
- Operating Humidity: 5-95% RH non condensing
- Compatible with 2GIG and Honeywell receivers
- Supervisory signal interval: 64 min(approx.)



Wirelessly monitor **ANY** single or linked UL listed hardwired smoke detector in a home by simply installing **ONE** FireFighter within 6 inches of any one of the existing smoke detectors.

